

FileWave Client Configuration

Essential so devices can contact the FileWave Server, with optional entries, but may require altering.

- [FileWave Custom Installer](#)
- [Superprefs Fileset](#)
- [FileWave Client Configuration Settings](#)

FileWave Custom Installer

Why

When installing the FileWave client on computers, it is necessary for the client to know certain information, for example, the FileWave Server address, whilst other information may also be useful to include: Boosters, Booster Routing, Enabling/Disabling Remote Connections, etc.

Similarly, when installing Boosters, they also require essential information including the FileWave Server and ports.

For this reason, the FileWave Custom Builder allows details to be entered and then for Clients download an MSI or PKG ready for provisioning devices or with Boosters there is the addition of creating a Debian custom installer.

When

Each of the installers could be used manually on devices, but the custom MSI is particularly useful when imaging Windows onto devices, whilst the custom PKG achieves the zero-touch enrolment for macOS and DEP.

Information

The FileWave Custom Installer is available via two URLs:

- <https://custom.filewave.com>
- <https://custom.filewave.ch>

Enter the details to match the FileWave Environment, e.g server's FQDN, Client or Booster version, etc. Once completed, hit the 'Build' button and FileWave will create the custom installer.

Superprefs Fileset

Description

When creating a Custom Client installer, client preferences are packaged inside the installer, e.g. server name, ports, Boosters, etc. However, it is not always the case that one set of preferences is appropriate for all devices.

Superprefs is a plist file, which can be deployed to macOS or Windows devices to alter settings.

The Custom Client installer could be considered to contain the base settings required. Multiple Superprefs Filesets could then be used to customise clients based upon, e.g., Smart Group criteria.

Alternatively, future changes may require alteration to the settings defined.

✔ This means, one single Superprefs Fileset can configure FileWave Clients en masse, when associated.

Ingredients

- FileWave Clients (macOS or Windows)
- FileWave Superprefs Editor
- FileWave Central Admin App

Directions

The process involves creating the Superprefs plist and then adding this into a Fileset for association with devices.

Superprefs Editor

Default installation of the editor is in the same location as the FileWave Central Admin Application:

macOS	/Applications/FileWave/Superprefs Editor.app
Windows	C:\Program Files (x86)\FileWave\FileWaveSuperPrefsEditor.exe

ℹ It is possible to edit current plist files. When opening the software a navigation window will open offering that choice. This may just be cancelled if creating a new Superprefs.

✔ Only items added/edited in the editor will be included in the plist file to deployed. All other items will be excluded. On deployment, only these included items will be set on the device; all other settings will remain untouched.

Example


Consider altering the Debug Level. Debug has 3 possible values:

10	Standard logging (default)
99	Debug logging
101	Trace logging

Imagine the desire to set Debug logging level on a client for further analysis.

After opening the editor and cancelling the Finder or Explorer window, there are several tabs to choose from. The Options tab contains the Debug Level. Set this as 99 and Save.

⚠ The name of the file must be: fwclد.newprefs.plist



The contents of the file should show as:

```
Dict {
  debugLevel = 99
}
```

As suggested, only the item altered in the editor has been saved to the file.

The fwcld.newprefs.plist file may be placed in any location within a Fileset, however consider where sensible locations could be.

For example:

macOS	/usr/local/etc/Superprefs/debug/fwcld.newprefs.plist
Windows	C:\ProgramData\FileWave\Superprefs\debug\fwcld.newprefs.plist

By creating a Superprefs folder, it makes it clear what this contains. By adding subfolders, it is then possible to have multiple subfolders with differing Superprefs if desired.

One Superprefs file could contain all desired changes or multiple files could be created for differing types of preferences.

The created file could be added to an existing Fileset, but it may be better to create a Fileset dedicated to this use. Taking the latter as an example.

Create Fileset

From the FileWave Central Admin Application:

- Create a new 'Empty' Fileset and name appropriately
- Open the Fileset and disable 'Hide unused folders'
- Select or create the desired location for the plist file
- Drag the file from Finder or Explorer into this location in the Fileset

Using the above Debug Log Level example for macOS, the Fileset could look like:

Superprefs Debug Logging225 B0

Fileset Contents: Superprefs Debug Logging

Import File/FolderNew FolderGet InfoEdit RegistryEdit TextExport FilesDeleteTake Control

Revision: <default> (Initial Revision)Manage Revisions

☒ Hide unused folders

Name	Size	Access	User	Group	Verification	ID
usr		rwXr-Xr-X	root	wheel		28997
local		rwXr-Xr-X	root	wheel		28998
etc		rwXr-Xr-X	root	wheel		29339
Superprefs		rwXr-Xr-X	root	wheel		155357
debug		rwXr-Xr-X	root	wheel		155358
fwcld.newprefs.plist	225 B	rw-r--r--	root	wheel	Self Healing	155359

When deployed to a client, the Debug Log Level should switch to 99 and the log file should reflect this change immediately on Fileset activation.

- ✔

Always test with one or a small subset of devices, before deploying further.
- ℹ

Consider making another similar Superprefs to return the device back to the Standard Log Level of 10, once analysis has been completed.

GUI Observation

When using the Superprefs Editor, some entries are Boolean, e.g. Booster Routing. As a Boolean entry there are only two possible values, True or False. Where a '-' is shown, this is standard GUI practice to indicate that the value is not set.

These preferences will be merged with the preferences on target clients.
If you would like a value to remain unchanged, leave it blank.

CommunicationsBoostersOptionsPrivacy

Personal Data

Collecting personal data may be disabled at an organization level.

-

Disable personal data collection

Location refresh interval:

Remote Sessions

-

Managed remote control

-

Prompt client for remote control access

With each press, one of three images will be shown:

	False
	True
	Unset

Configuration Settings

The following KB describes the possible FileWave Client settings:

- <https://kb.filewave.com/books/filewave-client/page/filewave-client-configuration-settings>

FileWave Client Configuration Settings

FileWave Client Configuration Settings

Configuration Settings are found in the Windows registry or macOS plist:

- macOS: `/usr/local/etc/fwclld.plist`
- Windows FileWave 15.4.2 or lower: `HKLM\Software\FileWave\WinClient` (32bit OS),
`HKLM\Software\FileWave\WOW6432\WinClient` (64bit OS)
- Windows FileWave 15.5.0 or higher: `HKLM\Software\FileWave\WOW6432\WinClient`

Please refer to [Creating a Superprefs Fileset](#) to find out how to change these settings on any number of clients using a fileset.

The following list shows the default settings in the left row, describes the function and valid alternative settings (native)

Basic/Minimal Configuration

server = "no.server.set"	FileWave server IP or DNS
primaryPort = 20015	FileWave Server Port
fwPassword = ""	Encrypted FileWave Client Password - used for remote configuration through client monitor
fwUser = my.filewave.client.name	FileWave Client name (visible in FileWave Admin)



Note: The default port setting above is 20015. However, SSL is now required, and the system will automatically use port 20017 instead when 20015 is entered. Do not manually set the port to 20017. Always enter 20015, and the system will handle the SSL port change for you.

Booster configuration

booster1 = "no.booster.set"	Booster 1 IP or DNS Address - When clearing the value it should be "no.booster.set"
booster1Port = 20013	Booster 1 Port - Should be 20013 by default when defining a booster
booster2 = "no.booster.set"	Booster 2 IP or DNS Address - When clearing the value it should be "no.booster.set"
booster2Port = 0	Booster 2 Port - Should be 20013 by default when defining a booster
booster3 = "no.booster.set"	Booster 3 IP or DNS Address - When clearing the value it should be "no.booster.set"
booster3Port = 0	Booster 3 Port - Should be 20013 by default when defining a booster
booster4 = "no.booster.set"	Booster 4 IP or DNS Address - When clearing the value it should be "no.booster.set"
booster4Port = 0	Booster 4 Port - Should be 20013 by default when defining a booster
booster5 = "no.booster.set"	Booster 5 IP or DNS Address - When clearing the value it should be "no.booster.set"
booster5Port = 0	Booster 5 Port - Should be 20013 by default when defining a booster
boosterRouting = 0	When set as 1, client connects to server through boosters, only for non HTTPS traffic (e.g. except for inventory / profile deployment) - 1 is recommended.
connectorProbeAttemptDelay = 3	Number of Seconds the client waits between trying to reach boosters
connectorProbeAttempts = 10	Number of unsuccessful connections that lead to booster being marked "offline"

TeamViewer (was Observe Client)

vncManaged = 0	Controls whether remote connection is allowed: * Teamviewer – FileWave 14.7+ * FileWave Client (fwclld) prior to 14.8
vncPromptClient = 1	Controls whether end user is prompted to allow remote connection: * Teamviewer – FileWave 14.7+ * FileWave Client (fwclld) prior to 14.8

Ports the client listens on

monitorPort = 20010	Client Monitor connects here, over the network * Only on Filewave 15.5.1 or lower
kioskPort = 20020	Kiosk / Reboot Dialog connects here, from localhost

Client behaviour

debugLevel = 10	Controls fwclld log verbosity; 10(normal),99(debug),101(trace)
fileCheckInterval = 86400	Number of seconds between verification cycles (default once every 24 hours after launch)
freeSpaceMargin = 2147483648	Minimum Number of free bytes left on disk so filesets can be deployed
setUsersFilesOwner = 1	Set ownership of Users files/folders to appropriate user
syncComputerName = 0	If set to 1, fwclld will query OS to retrieve computer name at startup, and use that as fwUser value
tickleInterval = 120	Number of seconds between attempts to contact FileWave Server for new Commands

Location Related

locationRefreshInterval = 0	If set to >0, number of seconds between querying the OS for location data
deviceState = 3	Client State, e.g.: Missing, Tracked, Untracked
denyPersonalDataCollection = 0	If set to 1, disables Location Services

Obsolete / Unused keys

testMode	
desktopOwner	
currentFileWaveClientName	
niceTime	
priority	
useSSL	
srvPublishPort = 20005	ZeroMQ messaging port (Deprecated from FileWave 14.8+. Removed from FileWave server 15.0 and notifications from earlier clients (pre 14.8) will no longer work at this point)
vncRelayPort = 20030	Port used to connect towards the filewave server to forward VNC Data (Deprecated from FileWave 14.8+)
vncServerPort = 20031	Local Port VNC Data is relayed to/from (set to 5900 to use builtin VNC service) (Deprecated from FileWave 14.8+)
booster1PublishPort = 20003	Booster 1 ZeroMQ prior to 14.8
booster2PublishPort = 0	Booster 2 ZeroMQ prior to 14.8
booster3PublishPort = 0	Booster 3 ZeroMQ prior to 14.8
booster4PublishPort = 0	Booster 4 ZeroMQ prior to 14.8
booster5PublishPort = 0	Booster 5 ZeroMQ prior to 14.8